



990 Response to a Load Tender

X12/V4010/990: 990 Response to a Load Tender

Version: 1.0

Company:

JR Simplot Company

Publication:

4/16/2012

Notes:

E-mail edi@simplot.com

Table of Contents

| | |
|-------------------------------------------------------------------|-----------|
| 990 Response to a Load Tender | 1 |
| ISA Interchange Control Header | 2 |
| GS Functional Group Header | 5 |
| ST Transaction Set Header | 7 |
| B1 Beginning Segment for Booking or Pick-up/Delivery | 8 |
| N9 Reference Identification | 9 |
| V9 Event Detail | 10 |
| K1 Remarks | 11 |
| SE Transaction Set Trailer | 12 |
| GE Functional Group Trailer | 13 |
| IEA Interchange Control Trailer | 14 |

990 Response to a Load Tender

Functional Group=GF

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Response to a Load Tender Transaction Set (990) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide general information relative to a specific shipment. The Response to a Load Tender is used as the response to a Motor Carrier Shipment Information Transaction Set (204) which has been used as a load tender.

Not Defined:

| <u>Pos</u> | <u>Id</u> | <u>Segment Name</u> | <u>Req</u> | <u>Max Use</u> | <u>Repeat</u> | <u>Notes</u> | <u>Usage</u> |
|------------|-----------|----------------------------|------------|----------------|---------------|--------------|--------------|
| | ISA | Interchange Control Header | M | 1 | | | Must use |
| | GS | Functional Group Header | M | 1 | | | Must use |

Heading:

| <u>Pos</u> | <u>Id</u> | <u>Segment Name</u> | <u>Req</u> | <u>Max Use</u> | <u>Repeat</u> | <u>Notes</u> | <u>Usage</u> |
|------------|-----------|---------------------------------------------------|------------|----------------|---------------|--------------|--------------|
| 010 | ST | Transaction Set Header | M | 1 | | | Must use |
| 020 | B1 | Beginning Segment for Booking or Pick-up/Delivery | M | 1 | | N1/020 | Must use |
| 030 | N9 | Reference Identification | O | 1 | | | Used |
| 050 | V9 | Event Detail | O | 10 | | | Used |
| 060 | K1 | Remarks | O | 10 | | | Used |
| 070 | SE | Transaction Set Trailer | M | 1 | | | Must use |

Not Defined:

| <u>Pos</u> | <u>Id</u> | <u>Segment Name</u> | <u>Req</u> | <u>Max Use</u> | <u>Repeat</u> | <u>Notes</u> | <u>Usage</u> |
|------------|-----------|-----------------------------|------------|----------------|---------------|--------------|--------------|
| | GE | Functional Group Trailer | M | 1 | | | Must use |
| | IEA | Interchange Control Trailer | M | 1 | | | Must use |

Notes:

1/020 ***Please do not return 990's for 204 Load Tenders that are replacements***

Transaction Examples:

SINGLE STOP SHIPMENT:

```
ST*990*7969
B1*SCAC*5759000*20151230*A
N9*CN*4455457
V9*ZZZ*S
SE*5*7969
```

MULTI-STOP LOAD:

```
ST*990*16000~
B1*SCAC*21363*20151217*A~
N9*CN*0311030~
V9*ZZZ*L
SE*4*16000~
```

ISA Interchange Control Header

| | |
|-------------------------|--------------|
| Pos: | Max: 1 |
| Not Defined - Mandatory | |
| Loop: N/A | Elements: 16 |

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> | | | | |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------|------------|-------------|----------------|--------------|-------------|-------------|----|-------------------------------------------------------------------------|
| ISA01 | I01 | Authorization Information Qualifier | M | ID | 2/2 | Must use | | | | |
| <p>Description: Code to identify the type of information in the Authorization Information</p> <p>CodeList Summary (Total Codes: 7, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>00</td> <td>No Authorization Information Present (No Meaningful Information in I02)</td> </tr> </tbody> </table> | | | | | | | <u>Code</u> | <u>Name</u> | 00 | No Authorization Information Present (No Meaningful Information in I02) |
| <u>Code</u> | <u>Name</u> | | | | | | | | | |
| 00 | No Authorization Information Present (No Meaningful Information in I02) | | | | | | | | | |
| ISA02 | I02 | Authorization Information | M | AN | 10/10 | Must use | | | | |
| <p>Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)</p> | | | | | | | | | | |
| ISA03 | I03 | Security Information Qualifier | M | ID | 2/2 | Must use | | | | |
| <p>Description: Code to identify the type of information in the Security Information</p> <p>CodeList Summary (Total Codes: 2, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>00</td> <td>No Security Information Present (No Meaningful Information in I04)</td> </tr> </tbody> </table> | | | | | | | <u>Code</u> | <u>Name</u> | 00 | No Security Information Present (No Meaningful Information in I04) |
| <u>Code</u> | <u>Name</u> | | | | | | | | | |
| 00 | No Security Information Present (No Meaningful Information in I04) | | | | | | | | | |
| ISA04 | I04 | Security Information | M | AN | 10/10 | Must use | | | | |
| <p>Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)</p> | | | | | | | | | | |
| ISA05 | I05 | Interchange ID Qualifier | M | ID | 2/2 | Must use | | | | |
| <p>Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified</p> <p>CodeList Summary (Total Codes: 38, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>12</td> <td>Phone (Telephone Companies)</td> </tr> </tbody> </table> | | | | | | | <u>Code</u> | <u>Name</u> | 12 | Phone (Telephone Companies) |
| <u>Code</u> | <u>Name</u> | | | | | | | | | |
| 12 | Phone (Telephone Companies) | | | | | | | | | |
| ISA06 | I06 | Interchange Sender ID | M | AN | 15/15 | Must use | | | | |
| <p>Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element</p> <p>Simplot Note: 2083848255</p> | | | | | | | | | | |
| ISA07 | I05 | Interchange ID Qualifier | M | ID | 2/2 | Must use | | | | |
| <p>Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified</p> | | | | | | | | | | |

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|----------------------------------------------------------------------------------------------------------------|
| | | CodeList Summary (Total Codes: 38, Included: 4) | | | | |
| | | Code Name | | | | |
| | | 01 | | | | Duns (Dun & Bradstreet) |
| | | 08 | | | | UCC EDI Communications ID (Comm ID) |
| | | 12 | | | | Phone (Telephone Companies) |
| | | ZZ | | | | Mutually Defined |
| ISA08 | I07 | Interchange Receiver ID | M | AN | 15/15 | Must use |
| | | Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them | | | | |
| ISA09 | I08 | Interchange Date | M | DT | 6/6 | Must use |
| | | Description: Date of the interchange | | | | |
| ISA10 | I09 | Interchange Time | M | TM | 4/4 | Must use |
| | | Description: Time of the interchange | | | | |
| ISA11 | I10 | Interchange Control Standards Identifier | M | ID | 1/1 | Must use |
| | | Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer | | | | |
| | | All valid standard codes are used. (Total Codes: 1) | | | | |
| ISA12 | I11 | Interchange Control Version Number | M | ID | 5/5 | Must use |
| | | Description: Code specifying the version number of the interchange control segments | | | | |
| | | CodeList Summary (Total Codes: 14, Included: 1) | | | | |
| | | Code Name | | | | |
| | | 00401 | | | | Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997 |
| ISA13 | I12 | Interchange Control Number | M | N0 | 9/9 | Must use |
| | | Description: A control number assigned by the interchange sender | | | | |
| ISA14 | I13 | Acknowledgment Requested | M | ID | 1/1 | Must use |
| | | Description: Code sent by the sender to request an interchange acknowledgment (TA1) | | | | |
| | | CodeList Summary (Total Codes: 2, Included: 1) | | | | |
| | | Code Name | | | | |
| | | 0 | | | | No Acknowledgment Requested |
| ISA15 | I14 | Usage Indicator | M | ID | 1/1 | Must use |
| | | Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information | | | | |
| | | CodeList Summary (Total Codes: 3, Included: 2) | | | | |
| | | Code Name | | | | |
| | | P | | | | Production Data |
| | | T | | | | Test Data |

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|------------------------------------|------------|-------------|----------------|--------------|
| ISA16 | I15 | Component Element Separator | M | | 1/1 | Must use |

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

GS Functional Group Header

| | |
|-------------------------|-------------|
| Pos: | Max: 1 |
| Not Defined - Mandatory | |
| Loop: N/A | Elements: 8 |

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| GS01 | 479 | Functional Identifier Code | M | ID | 2/2 | Must use |
| | | Description: Code identifying a group of application related transaction sets | | | | |
| | | CodeList Summary (Total Codes: 240, Included: 1) | | | | |
| | | Code Name | | | | |
| | | GF Response to a Load Tender (990) | | | | |
| GS02 | 142 | Application Sender's Code | M | AN | 2/15 | Must use |
| | | Description: Code identifying party sending transmission; codes agreed to by trading partners | | | | |
| GS03 | 124 | Application Receiver's Code | M | AN | 2/15 | Must use |
| | | Description: Code identifying party receiving transmission; codes agreed to by trading partners | | | | |
| | | Simplot Note: 2083848255 | | | | |
| GS04 | 373 | Date | M | DT | 8/8 | Must use |
| | | Description: Date expressed as CCYYMMDD | | | | |
| GS05 | 337 | Time | M | TM | 4/8 | Must use |
| | | Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99) | | | | |
| GS06 | 28 | Group Control Number | M | NO | 1/9 | Must use |
| | | Description: Assigned number originated and maintained by the sender | | | | |
| GS07 | 455 | Responsible Agency Code | M | ID | 1/2 | Must use |
| | | Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480 | | | | |
| | | CodeList Summary (Total Codes: 2, Included: 1) | | | | |
| | | Code Name | | | | |
| | | X Accredited Standards Committee X12 | | | | |
| GS08 | 480 | Version / Release / Industry Identifier Code | M | AN | 1/12 | Must use |
| | | Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions | | | | |

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| | | 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed | | | | |
| | | CodeList Summary (Total Codes: 39, Included: 1) | | | | |
| | | Code Name | | | | |
| | | 004010 Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997 | | | | |

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

| | |
|---------------------|-------------|
| Pos: 010 | Max: 1 |
| Heading - Mandatory | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------|----------------------------------------|------------|-------------|----------------|--------------|
| ST01 | 143 | Transaction Set Identifier Code | M | ID | 3/3 | Must use |
| Description: Code uniquely identifying a Transaction Set | | | | | | |
| CodeList Summary (Total Codes: 298, Included: 1) | | | | | | |
| Code Name | | | | | | |
| 990 Response To a Load Tender | | | | | | |
| ST02 | 329 | Transaction Set Control Number | M | AN | 4/9 | Must use |
| Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set | | | | | | |

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

B1 Beginning Segment for Booking or Pick-up/Delivery

| | |
|---------------------|-------------|
| Pos: 020 | Max: 1 |
| Heading - Mandatory | |
| Loop: N/A | Elements: 4 |

User Option (Usage): Must use

Purpose: To transmit identifying numbers, dates, and other basic data relating to the transaction set

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| B101 | 140 | Standard Carrier Alpha Code Description: Standard Carrier Alpha Code | O | ID | 2/4 | Used |
| B102 | 145 | Shipment Identification Number Description: Identification number assigned to the shipment by the shipper that uniquely identifies the shipment from origin to ultimate destination and is not subject to modification; (Does not contain blanks or special characters) Simplot Note: <i>Simplot's single-stop shipment number or multi-stop load number.</i> | M | AN | 1/30 | Must use |
| B103 | 373 | Date Description: Date expressed as CCYYMMDD | M | DT | 8/8 | Must use |
| B104 | 558 | Reservation Action Code Description: Code identifying action on reservation or offering CodeList Summary (Total Codes: 7, Included: 2) Code Name A Reservation Accepted D Reservation Cancelled | M | ID | 1/1 | Must use |

Semantics:

1. B101 is the Standard Carrier Alpha Code (SCAC) of the carrier sending the EDI transmission.
2. B103 is the booking date accepted by the carrier.

N9 Reference Identification

| | |
|--------------------|-------------|
| Pos: 030 | Max: 1 |
| Heading - Optional | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------|-------------------------------------------|------------|-------------|----------------|--------------|
| N901 | 128 | Reference Identification Qualifier | M | ID | 2/3 | Must use |
| <p>Description: Code qualifying the Reference Identification</p> <p>CodeList Summary (Total Codes: 1503, Included: 1)</p> <p>Code Name</p> <p>CN Carrier's Reference Number (PRO/Invoice)</p> | | | | | | |
| N902 | 127 | Reference Identification | X | AN | 1/30 | Used |
| <p>Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier</p> | | | | | | |

Not required if load is rejected

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

Simple Note:

N9 is not required if shipment/load is rejected.

V9 Event Detail

| | |
|--------------------|-------------|
| Pos: 050 | Max: 10 |
| Heading - Optional | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Used

Purpose: To specify information about a specific event

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> | | | | |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|---------------------|------------|-------------|----------------|--------------|-------------|-------------|-----|------------------|
| V901 | 304 | Event Code | O | ID | 3/3 | Used | | | | |
| <p>Description: Code identifying the event about which a report is made</p> <p>CodeList Summary (Total Codes: 104, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>ZZZ</td> <td>Mutually Defined</td> </tr> </tbody> </table> | | | | | | | <u>Code</u> | <u>Name</u> | ZZZ | Mutually Defined |
| <u>Code</u> | <u>Name</u> | | | | | | | | | |
| ZZZ | Mutually Defined | | | | | | | | | |
| V902 | 106 | Event | O | AN | 1/25 | Used | | | | |
| <p>Description: Free-form description of event</p> <p>Simplot Note: Send "S" for single-stop shipment. Send "L" for multi-stop load.</p> | | | | | | | | | | |

Syntax Rules:

1. P1011 - If either V910 or V911 is present, then the other is required.
2. C1304 - If V913 is present, then V904 is required.
3. C1509 - If V915 is present, then V909 is required.

Semantics:

1. V903 is the event date.
2. V904 is the event time.
3. V909 is the Standard Point Location Code (SPLC) of the event shown in the V901.
4. V910 is the length of the time delay expressed in hours.
5. V913 reflects the time zone which the event time reflects.
6. V914 is the quantity of the fuel in gallons.
7. V915 is the Standard Point Location Code (SPLC) of the secondary point of the delay indicated in the V911.
8. V916 is the total number of rail cars associated with the event code in V901.
9. V917 is the total number of loaded cars associated with the event code in V901.
10. V918 is the total number of empty cars associated with the event code in V901.
11. V919 is the total Gross Tons of the cars identified in V916. Includes the gross weight of the loads and the tare weight of the empties.
12. V920 is the total outside foot length of the cars identified in V916, rounded off to the nearest foot.

K1 Remarks

| | |
|---------------------------|--------------------|
| Pos: 060 | Max: 10 |
| Heading - Optional | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Used

Purpose: To transmit information in a free-form format for comment or special instruction

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|-------------------------------------------|------------|-------------|----------------|--------------|
| K101 | 61 | Free-Form Message | O | AN | 1/30 | Used |
| | | Description: Free-form information | | | | |
| K102 | 61 | Free-Form Message | O | AN | 1/30 | Used |
| | | Description: Free-form information | | | | |

SE Transaction Set Trailer

| | |
|---------------------|-------------|
| Pos: 070 | Max: 1 |
| Heading - Mandatory | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| SE01 | 96 | Number of Included Segments | M | N0 | 1/10 | Must use |
| | | Description: Total number of segments included in a transaction set including ST and SE segments | | | | |
| SE02 | 329 | Transaction Set Control Number | M | AN | 4/9 | Must use |
| | | Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set | | | | |

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

| | |
|-------------------------|-------------|
| Pos: | Max: 1 |
| Not Defined - Mandatory | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| GE01 | 97 | Number of Transaction Sets Included | M | N0 | 1/6 | Must use |
| | | Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element | | | | |
| GE02 | 28 | Group Control Number | M | N0 | 1/9 | Must use |
| | | Description: Assigned number originated and maintained by the sender | | | | |

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

| | |
|-------------------------|-------------|
| Pos: | Max: 1 |
| Not Defined - Mandatory | |
| Loop: N/A | Elements: 2 |

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

| <u>Ref</u> | <u>Id</u> | <u>Element Name</u> | <u>Req</u> | <u>Type</u> | <u>Min/Max</u> | <u>Usage</u> |
|------------|-----------|-------------------------------------------------------------------------------------------|------------|-------------|----------------|--------------|
| IEA01 | I16 | Number of Included Functional Groups | M | NO | 1/5 | Must use |
| | | Description: A count of the number of functional groups included in an interchange | | | | |
| IEA02 | I12 | Interchange Control Number | M | NO | 9/9 | Must use |
| | | Description: A control number assigned by the interchange sender | | | | |